

KUEBLER - ABSOLUTE-CODED ANGULAR TRANSMITTER SENDIX F3653 / F3673, OPTICAL, SSI, Ø36 MM SERIE F3653

- Housing diameter Ø36 mm
- SSI-Interface
- 17 bit resolution
- -40 to +90 ° C working temperature



Product description

Sendix F3653 / F3673 is a series of single-axis optical axial and hole axle outputs with SSI interface and a resolution of up to 17 bits, despite its compact size of 36x42 mm. The sensor also has high enclosure class, shock resistance and a wide temperature range. The sensor is therefore very suitable for applications where extreme environments or temperatures can occur, such as mobile applications. The sensor is supplied with a tangential cable, which means that there is no exposed cable input on the sensor, but it is embedded in the housing itself to increase impact on impact and impact. The Sendix F3653 / F3673 is also available in a salt water resistant version.

Please refer to the images below for ordering information.

Order code	8.F3653 . XXXXX . XX12					
Shaft version	Type	a	b	c	d	e
a Flange						
1 = clamping flange, IP67, ø 36 mm [1.42"]						
3 = clamping flange, IP65, ø 36 mm [1.42"]						
2 = synchro flange, IP67, ø 36 mm [1.42"]						
4 = synchro flange, IP65, ø 36 mm [1.42"]						
b Shaft (ø x L), with flat						
1 = ø 6 x 12.5 mm [0.24 x 0.49"]						
3 = ø 8 x 15 mm [0.32 x 0.59"]						
5 = ø 10 x 20 mm [0.39 x 0.79"]						
2 = ø 1/4" x 12.5 mm [0.49"]						
4 = ø 3/8" x 5/8"						
c Interface / power supply						
1 = SSI, BiSS / 5 V DC						
2 = SSI, BiSS / 10 ... 30 V DC						
3 = SSI, BiSS + 2048 ppr. SinCos / 5 V DC						
4 = SSI, BiSS + 2048 ppr. SinCos / 10 ... 30 V DC						
5 = SSI, BiSS / 5 V DC, with sensor output						
6 = SSI, BiSS + 2048 ppr. SinCos / 5 V DC, with sensor output						
7 = SSI, BiSS + 2048 ppr. RS422 / 5 V DC						
8 = SSI, BiSS + 2048 ppr. RS422 / 10 ... 30 V DC						
d Type of connection						
1 = tangential cable, 1 m [3.28] PUR						
3 = tangential cable, 5 m [16.40] PUR						
F = tangential cable, special length PUR *)						
8 = axial M12 connector, 8-pin ¹⁾						
*) Available special lengths (connection type F): 2, 3, 8, 10, 15 m [6.56, 9.84, 26.25, 32.80, 49.21'] order code expansion .XXXX = length in dm ex.: 8.F3653.432F.G312.0030 (for cable length 3 m)						
e Code						
B = SSI, binary						
C = BiSS, binary						
G = SSI, gray						
f Resolution						
A = 10 bit						
2 = 12 bit						
3 = 13 bit						
4 = 14 bit						
7 = 17 bit						
<i>Optional on request</i>						
- surface protection						
- salt spray tested						
- other resolutions						

Order code
Hollow shaft

8.F3673 . **XXXX** . **XX12**
Type **a** **b** **c** **d** **e** **f**

a Flange

- 1 = with spring element, short, IP65
- 3 = with spring element, long, IP65
- 2 = with stator coupling, IP65, ø 46 mm [1.81"]**

b Through hollow shaft

- 1 = ø 6 mm [0.24"]
- 3 = ø 8 mm [0.32"]
- 2 = ø 1/4"
- Blind hollow shaft
(insertion depth max. 14.5 mm [0.57"])
- 4 = ø 10 mm [0.39"]**

c Interface / power supply

- 1 = SSI, BiSS / 5 V DC
- 2 = SSI, BiSS / 10 ... 30 V DC**
- 3 = SSI, BiSS + 2048 ppr. SinCos / 5 V DC
- 4 = SSI, BiSS + 2048 ppr. SinCos / 10 ... 30 V DC
- 5 = SSI, BiSS / 5 V DC, with sensor output
- 6 = SSI, BiSS + 2048 ppr. SinCos / 5 V DC, with sensor output
- 7 = SSI, BiSS + 2048 ppr. RS422 / 5 V DC
- 8 = SSI, BiSS + 2048 ppr. RS422 / 10 ... 30 V DC

d Type of connection

- 1 = tangential cable, 1 m [3.28] PUR**
 - 3 = tangential cable, 5 m [16.40] PUR
 - F = tangential cable, special length PUR *)
 - 8 = axial M12 connector, 8-pin ¹⁾
- *) Available special lengths (connection type F):
2, 3, 8, 10, 15 m [6.56, 9.84, 26.25, 32.80, 49.21']
order code expansion .XXXX = length in dm
ex.: 8.F3673.242FG312.0030 (for cable length 3 m)

e Code

- B = SSI, binary
- C = BiSS, binary
- G = SSI, gray**



f Resolution

- A = 10 bit
- 2 = 12 bit
- 3 = 13 bit**
- 4 = 14 bit
- 7 = 17 bit

Optional on request
- surface protection
- salt spray tested
- other resolutions

Specifications

Housing diameter	36
IP Class	IP65, IP67
Shaft Diameter max	10
Shaft Diameter min	6
Supply Voltage DC Max	30
Supply Voltage DC Min	5
Temperature range from	-40
Temperature range to	90



Terminal assignment


Interface	Type of connector	Features	Cable
1, 2	1, 3	SSI or BiSS, SET DIR, Status	Signal: GND +V -C -C +D -D SET DIR Stat PE Cable colour: WH BN GN YE CY PK BU RD VT Shield
Interface	Type of connector	Features	Cable
1, 2	5	SSI or BiSS, SET DIR	Signal: GND +V -C -C +D -D SET DIR ShieldPE M12 connector: 1 2 3 4 5 6 7 8
Interface	Type of connector	Features	Cable
3, 4	1, 3	SSI or BiSS, SET DIR, 2048 SinCos	Signal: GND +V -C -C +D -D SET DIR A A inc B B inc PE Cable colour: WH BN GN YE CY PK BU RD BK VT CHFN RD BU Shield
Interface	Type of connector	Features	Cable
5	1, 3	SSI or BiSS, SET DIR, Sensor outputs	Signal: GND +V -C -C +D -D SET DIR GND _{inc} +V _{inc} PE Cable colour: WH BN GN YE CY PK BU RD BK VT RD BU Shield
Interface	Type of connector	Features	Cable
6	1, 3	SSI or BiSS, 2048 SinCos, Sensor outputs	Signal: GND +V -C -C +D -D GND _{inc} +V _{inc} A A inc B B inc PE Cable colour: WH BN GN YE CY PK BU RD BK VT CHFN RD BU Shield
Interface	Type of connector	Features	Cable
X, 8	1, 3	SSI or BiSS, 2048 incr. RS422	Signal: GND +V -C -C +D -D A A inc B B inc PE Cable colour: WH BN GN YE CY PK BK VT CHFN RD BU Shield

+V Encoder power supply +V DC
GND Encoder power supply ground (0V)
-C- Clock signal
+D- Data signal
SET Set input. The current position becomes defined as position zero.
DIR Direction input. If this input is active, output values are counted backwards (decreases when the shaft is turning clockwise).
Stat Status output
PE Protective earth
Pin Plug connector housing shield
A, A inc Incremental output channel A
B, B inc Incremental output channel B

Top view of mating side, male contact base



M12 connector, 8-pin



Terminal assignment

Interface	Type of connector	Features	Cable
1,2	1,3	ISO or BISS, SET DIR, Status	Signal: GND +V -C -D SET DIR Stat PE Cable colour: WH BN GN YE GY PK BU RD VT Shield
1,2	5	ISO or BISS, SET DIR	Signal: GND +V -C -D SET DIR Shield PE M12 connector: 1 2 3 4 5 6 7 8 Pin
3,4	1,3	ISO or BISS, SET DIR, 2048 SinCos	Signal: GND +V -C -D SET DIR A Ainc B Binc PE Cable colour: WH BN GN YE GY PK BU RD VT (GY,PK,BU) Shield
5	1,3	ISO or BISS, SET DIR, Status outputs	Signal: GND +V -C -D SET DIR GNDinc +Vinc PE Cable colour: WH BN GN YE GY PK BU RD VT RO BU Shield
6	1,3	ISO or BISS, 2048 SinCos Status outputs	Signal: GND +V -C -D SET DIR GNDinc +Vinc A Ainc B Binc PE Cable colour: WH BN GN YE GY PK BU RD BK VT (GY,PK,BU) Shield
2,8	1,3	ISO or BISS, 2048 inc. RS422	Signal: GND +V -C -D A Ainc B Binc PE Cable colour: WH BN GN YE GY PK BK VT (GY,PK) RO BU Shield

+V Encoder power supply +V DC
 GND Encoder power supply ground GND (0V)
 -C Click signal
 -D Data signal
 SET Set input. The current position becomes defined as position zero.
 DIR Direction input. If this input is active, output values are counted backwards (decrease) when the shaft is turning clockwise.
 Stat Status output
 PE Protective earth
 Pin Plug connector housing (Shell)
 A, A inc Incremental output channel A
 B, B inc Incremental output channel B

Top view of mating side, male contact base



M12 connector, 8-pin